


# Applications

## Call Flows

Direct calls between two destinations by calling a feature code.

### Call Flows

Direct calls between two destinations by calling a feature code.

Status	Extension	Feature Code	Description	
Day Mode	30	*30	Label what this call flow does.	 

- **Name:** Define the name of the call flow.
- **Extension:** Define what extension to use. (This will make an extension not already created)
- **Feature Code:** Define what \* number to use
- **Context:** Domain context (typically leave as is)
- **Status:** Define what currently is in use.
- **Pin Number:** Define a pin number in order to execute either mode.
- **Destination:** Define where the call will go in the initial mode.
- **Sound:** Define the sound that will play once mode is engaged.
- **Destination:** Define what the destination will be.
- **Alternative Label:** Label that will show when alternative mode is in use.
- **Alternative Sound:** Define the sound that will play once alternative mode is engaged.
- **Alternative Destination:** Define where the call will go in the alternative mode.
- **Description:** Label what this call flow does.









## Call Flow Example

In the Call Flow example below we have the name as Call Flow. Make the Extension number 30 that didn't exist until now. Create the feature code as a \*code with \*30. Keep the context as-is with [training.fusionpbx.com](https://training.fusionpbx.com). Select a Status to show which mode. Make a PIN to help secure the call flow. Make the destination label as Day Mode. Select a sound to auditorially indicate which mode is activated. Choose a destination for the alternative mode. Make the alternative destination label as Night Mode. Select an alternative sound to auditorially indicate which mode is activated. Choose a destination for the alternative mode. Finally, enter a description to describe what this call flow does.

# Applications

## Call Flow

BACK SAVE

Name	<input type="text" value="Call Flow"/>
	Enter the name.
Extension	<input type="text" value="30"/>
	Enter the extension number.
Feature Code	<input type="text" value="*30"/>
	Enter the feature code.
Context	<input type="text" value="training.fusionpbx.com"/> 
	Enter the context.
Status	<input type="text" value="Day Mode"/> 
	Select the status.
PIN Number	<input type="text" value="8675309"/>
	Enter the pin number.
Destination Label	<input type="text" value="Day Mode"/>
Sound	<input type="text" value="ivr/ivr-day_mode.wav"/> 
	Select the sound to play when the status is set to the destinations.
Destination	<input type="text" value="104"/>  
	Select the destination.
Alternate Label	<input type="text" value="Night Mode"/>
	Enter the alternate destination label.
Alternate Sound	<input type="text" value="ivr/ivr-night_mode.wav"/> 
	Select the sound to play when status is set to the alternate destination.
Alternate Destination	<input type="text" value="101"/>  
	Select the alternate destination.
Description	<input type="text" value="Label what this call flow does."/>

SAVE

Unieke FAQ ID: #4010  
Auteur: Helpdesk  
Laatst bijgewerkt:2022-10-31 01:12