

## 3CX - Fritzbox telefonie configuratie

Deze instructie is voor het configureren van de fritzbox telefonie functies voor een 3CX server.

Configureer de fritzbox naar onderstaand voorbeeld.

Navigeer naar **Telephony > Telephony Numbers**

Bewerk een **bestaand nummer** of klik op **New telephony number** om een nieuwe toe te voegen.

### Telephony Numbers:

☒ Use Internet telephone number

Telephony provider

Other provider

Telephone Number for  
Registration\*

Internal Telephone Number in  
the FRITZ!Box\*

Display name

205

205



Other Telephone Numbers

#### \*Telephone Number for Registration

Please enter in this column the telephone number for registration. You received this telephone number from your provider. Different providers may call it by a different name. Please enter the telephone number exactly as you received it from the provider, including any special characters it may include.

#### \*Internal Telephone Number in the FRITZ!Box

Now enter your telephone number without an area code and without special characters.

#### Other Telephone Numbers

Under "Other Telephone Numbers" you can create additional telephone numbers, as long as they have same account information (user name and password) as the first telephone number. Telephone numbers with other account information can be configured later using the "New Telephone Numbers" button under "Telephone Numbers".

### Account Information:

# 3CX

User name	<input type="text" value="Zie 3CX Authentication ID"/>
Password	<input type="text" value="Zie 3CX Authentication Password"/>
Registrar	<input type="text" value="3cxservername.3cx.eu:5060"/>
Proxy server	<input type="text"/>
STUN server	<input type="text" value="3cxservername.3cx.eu:5060"/>

## Telephone Number Format

Precede the number dialed with these prefix numerals:

Country code	<input checked="" type="radio"/> None	<input type="radio"/> Without prefix (31)	<input type="radio"/> With prefix (0031)
Area code	<input checked="" type="radio"/> None	<input type="radio"/> Without prefix	<input type="radio"/> With prefix (0)

☒ Relay outgoing emergency calls without prefixes

☒ Relay special rate numbers without prefixes

☐ Telephony provider with North American number plan (NANP)  
(international prefix 011 instead of 00)

☐ Relay local telephone number in international telephone number format

Suffix for Internet telephone numbers

## Additional Settings:

DTMF transmission	<input type="text" value="Automatically"/>
Suppress outgoing Caller ID (CLIR)	<input type="text" value="CLIR via display name"/>
Caller ID	<input type="text" value="Disabled"/>

☒ Use telephone number for registration

☐ Provider supports call-back on busy (CCBS) in accordance with RFC 4235

Packet size in milliseconds in send direction

☒ Always register via an Internet connection  
If your Internet provider reserves a separate Internet connection for your own telephone numbers, enable this option for any telephone numbers from another provider.

☒ Provider supports MWI (RFC 3842)

☐ Provider does not support REGISTER-fetch

Enter your area code:

Area code

Unieke FAQ ID: #3966

Auteur:

Laatst bijgewerkt: 2022-05-10 11:36