

Applications

Call Broadcast

Broadcast calls (a light dialer) to a defined list of phone numbers.

Call Broadcasts

Name	Concurrent Limit	Description	
Dialer Light	5	Dialer Light	   

- To create a call broadcast click the **plus** on the right

Fill in the following fields

- **Name-** Name for the Call Broadcast.
- **Accountcode** Used by some billing systems.
- **Timeout-** Amount of time till hangup.
- **Concurrent Limit-** Used to pace the calls calls if the timeout was 60 and the concurrent

limit is 100 then we would schedule 100 calls every 60 seconds.

- **Caller ID Name-** Name that will be used on outbound caller id.
- **Caller ID Number-** Number that will be used on outbound caller id.
- **Destination Number-** This is the internal number to call. Send the call to an IVR Menu or

some other number. If sending to a conference room make sure the room has a pin number or something that requires user input you don't want to add voicemail messages into the conference room.

For example *9198

- **Phone Number List-** List of phone numbers to call in the call broadcast.

This is the external number to call. Set a list of phone numbers one per row in the following format:
123-123-1234|Last Name, First Name

5551231234|example 1

5551231234|example 2

5551231234|example 3

- **Voicemail Detection-** Set **True or false** to detect an answering machine.
- **Description** Help organize and label what the call broadcast is for.

Applications

Call Broadcast

[BACK](#) [SEND BROADCAST](#) [STOP BROADCAST](#) [SAVE](#)

Name	<input type="text" value="Dialer Light"/> <small>Enter the name here.</small>
Accountcode	<input type="text"/>
Timeout	<input type="text" value="30"/>
Concurrent Limit	<input type="text" value="5"/> <small>Limit the approximate number of concurrent calls. Leave this empty for no limit.</small>
Caller ID Name	<input type="text" value="Dialer Light"/> <small>Applicable if the provider allow the Caller ID Name to be set. default: anonymous</small>
Caller ID Number	<input type="text" value="5558675309"/> <small>Applicable if the provider that allow the Caller ID number to be sent. default: 0000000000</small>
Destination Number	<input type="text" value="1010"/> <small>Send the call to the extension an IVR Menu, Conference Room, or any other number.</small>
Phone Number List	<input type="text" value="555-123-1234"/> 555-123-1235 555-123-1236 <small>Optional, set a list of phone numbers one per row in the following format: 123-123-1234 Last Name, First Name</small>
Voicemail Detection	<input type="text" value="True"/> <input type="button" value="v"/> <small>Select whether to enable or disable the detection of voicemail messaging and answering machine systems.</small>
Description	<input type="text" value="Dialer Light"/> <small>Enter the description here.</small>

[SAVE](#)

- Once you have everything filled out click the **Call Broadcast name** you just created. On the top right click the **Send Broadcast** button to start the call broadcast. To stop the call broadcast click **STOP BROADCAST** on the top right.

Uses [sched_api](#) to schedule an API call in the future. Is used to schedule calls to the provided number/extensions and send them to the extension an IVR Menu, Conference Room, or any other number. Could be used among other things to schedule a Conference.

[Next](#) [Previous](#)

Unieke FAQ ID: #4007

Auteur: Helpdesk

Laatst bijgewerkt: 2022-10-31 01:11