

Gigaset

Instellen SIP account op de Gigaset N300a IP

Deze instructie is voor het instellen van de Gigaset N300A voor het gebruik van VOIP telefonie.

Stap 1. Inloggen op het basisstation

Zoek het IP adres van het basisstation op in het handset.

Op de Gigaset handset gaat u naar:

Settings -> Base -> Local Network.

Onder het IP Address ziet u het ip van het basisstation staan.

Voer dit IP adres in in uw internetbrowser (bijvoorbeeld Google Chrome)

Standaard is de PIN: 0000



Stap 2. Instellen provisioning

Navigeer naar: Settings -> Telephony -> Connections en druk achter IP1 op Edit

Druk vervolgens op Show Advanced Settings en vul het volgende in:

Authentication name: Inlognaam extensie

Authentication password: Wachtwoord extensie

Display name: Gewenste displaynaam

Domain: pbx.business-isp.nl

Proxy server address: pbx.business-isp.nl

Gigaset

STUN enabled: Yes

STUN server address stun.business-isp.nl

Zodra u alles heeft ingevuld, druk dan op Set en vervolgens op Update Profile

Hieronder ziet u een voorbeeld van de instellingen

Gigaset N300A IP

[Log Off](#)
[Home](#)
[Settings](#)
[Status](#)
[Network](#)
[Telephony](#)
[Connections](#)
[Audio](#)
[Number Assignment](#)
[Call Divert](#)
[Dialling Plans](#)
[Network Mailboxes](#)
[Advanced VoIP settings](#)
[Messaging](#)
[Info Services](#)
[Directories](#)
[Management](#)

1. IP Connection

Assign a connection name or actual phone number for identification.

Connection Name or Number:

VoIP Configuration / Profile Download

[Start Configuration Assistant](#)

Provider:

Profile Version

Personal Provider Data

Authentication name:

Authentication password:

Username:

Display name:

[Hide Advanced Settings](#)

General data of your service provider

Domain:

Proxy server address:

Proxy server port:

Registration server:

Registration server port:

Registration refresh time:

 sec

Network data for your service provider

STUN enabled:

☐ Yes ☒ No

STUN server address:

STUN server port:

STUN refresh time:

 sec

NAT refresh time:

 sec

Outbound proxy mode:

☐ Always ☐ Automatic ☒ Never

Outbound server address:

Outbound proxy port:

[Set](#)
[Cancel](#)
[Delete Connection](#)

Stap 3. Number Assignment

Gigaset

Navigeer naar: Settings -> Telephony -> Number Assignment .

Op het toestel kunt u zien welke naam uw handset heeft. Als voorbeeld nemen wij INT 1.

Voer bij Name uw gewenste naam in die op het display komt te staan. In dit geval gebruiken wij: 201-klant.

zorg ervoor dat het bolletje en het vinkje gevult is (door erop te drukken) bij hetgeen dat u bij vorige stap hebt ingevuld bij Connection name or number.

The screenshot shows the Gigaset N300A IP web interface. The top navigation bar includes 'Home', 'Settings', and 'Status'. The left sidebar lists various settings categories: Network, Telephony, Connections, Audio, Call Divert, Dialling Plans, Network Mailboxes, Advanced VoIP settings, Messaging, Info Services, Directories, and Management. The 'Number Assignment' option under 'Audio' is highlighted with a red box. The main content area displays the 'Handsets' configuration. A red box highlights the settings for 'INT 1'. The instructions at the top of the main area state: 'Select the connection for outgoing calls and also one or more connections for incoming calls for each handset.' The 'INT 1' configuration includes a 'Name' field with the value '201-klant'. Below this is a table with columns for 'Connection', 'for outgoing calls', and 'for incoming calls'. The table lists several connections: '201-klant #10', 'INT 2 #11', 'INT 3 #12', 'Gigaset.net', and 'Fixed Line'. The '201-klant #10' connection is selected for outgoing calls (radio button) and has a checked checkbox for incoming calls. The 'Select line for each outgoing call' option is also visible. The 'INT 2' configuration is partially visible below, showing a 'Name' field and a table with '201-klant #10' and 'Zolder #11' connections.

Connection	for outgoing calls	for incoming calls
201-klant #10	<input checked="" type="radio"/>	<input checked="" type="checkbox"/>
INT 2 #11	<input type="radio"/>	<input type="checkbox"/>
INT 3 #12	<input type="radio"/>	<input type="checkbox"/>
Gigaset.net	<input type="radio"/>	<input type="checkbox"/>
Fixed Line	<input type="radio"/>	<input type="checkbox"/>

U kunt nu bellen met uw dect toestel.

Unieke FAQ ID: #1223

Auteur: Helpdesk

Laatst bijgewerkt: 2015-09-24 15:45