

Gebruikers dashboard

Aanpassingen Grandstream toestel via PBX Manager

Deze instructie beschrijft het instellen van enkele specifieke instellingen voor op Grandstream toestellen via de PBX Manager.

Instructie:

Navigeer naar Accounts > Devices

Klik op de regel van het betreffende device / toestel.

Onder Settings kunnen specifieke waardes ingesteld worden.

Voorbeeld:

Settings	Name	Value	Enabled	Description	Delete
	grandstream_auto_i	0	True ▼	Blind Transfer	<input type="checkbox"/>
	grandstream_displa	nl	True ▼	Display Language	<input type="checkbox"/>
			True ▼		

Hieronder een lijst met de beschikbare opties:

Name	Value	Description	Default
grandstream_display_language	nl	Display Language	en
grandstream_auto_attended_transfer	0	Transfer Method	Blind Transfer
grandstream_call_waiting	1	Uitschakelen wisselgesprek	0
grandstream_speaker_ring_volume	1 t/m 7	Instellen vast ring tone volume	Device setting
grandstream_lan_port_vlan	0 t/m 4095	VLAN ID toestel	0
grandstream_pc_port_vlan	0 t/m 4095	VLAN ID PC poort	0
grandstream_wifi_ssid		WiFi SSID	
grandstream_wifi_password		WiFi Password	

Gebruikers dashboard

ssword
grandstream Zie ve _firmware_pa rsies th

Firmware versies:

pbxconfig.business-isp.nl/app/grandstream/resources/firmware/Release_GXP2130_1.0.7.97
pbxconfig.business-isp.nl/app/grandstream/resources/firmware/Release_GXP2130_1.0.8.56
pbxconfig.business-isp.nl/app/grandstream/resources/firmware/Release_GXP2130_1.0.9.135
pbxconfig.business-isp.nl/app/grandstream/resources/firmware/Release_GXP2135_1.0.7.97
pbxconfig.business-isp.nl/app/grandstream/resources/firmware/Release_GXP2135_1.0.8.56
pbxconfig.business-isp.nl/app/grandstream/resources/firmware/Release_GXP2135_1.0.9.135

Unieke FAQ ID: #4069

Auteur:

Laatst bijgewerkt:2022-11-04 00:00