### **Outbound Routes**

Route outbound calls to gateways, tdm, enum and more. When a call matches the conditions the call to outbound routes. <u>Check out the youtube video</u>.

#### Configuring an Outbound Route.

- Select **Dialplan** from the drop-down list and then click **Outbound Routes** .
- Click the **plus** button on the right. Enter the route information below and Click **Save** once entry is complete.

Outbound	Routes		SEARCH			
Route outbo the conditior	und calls to gatewa is the call to outbou	ys, tdm, enum and mo nd routes.	ore. When a call ma	tches		
Name	Number	Context	Order	Enabled	Description	
						-5

#### Outbound Routes

Outbound dialplans have one or more conditions that are matched to attributes of a call. When a call matches the conditions the call is then routed to the gateway.

Gateway	VoiceTel Select the gateway to use with this outbound route.
Alternate 1	Select another gateway as an alternative to use if the first one fails.
Alternate 2	Select another gateway as an alternative to use if the second one fails.
Dialplan Expression	^\+?1?(\d{10})\$
Prefix	Enter a prefix number to add to the beginning of the destination number.
Limit	Enter limit to restrict the number of outbound calls.
Account Code	Enter the accountcode.
Order	Select the order number. The order number determines the order of the outbound routes when there is more than one.
Enabled	True Choose to enable or disable the outbound route.
Description	Enter a description, if desired.

Gateway: VoiceTel Dialplan Expression: ^(?:\+?1)?(\d{10})\$ (You can also choose more than one from the drop down list also as needed) Order: 000 Enabled: true

#### Pagina 2 / 4

© 2024 Business-ISP <support@business-isp.nl> | 08-05-2024 23:47

URL: https://faq.business-isp.nl/index.php?action=faq&cat=127&id=3004&artlang=nl

BACK SAVE

#### By using <u>VoiceTel</u> you help support FusionPBX. Thank you for your support!

### **Pin Numbers**

To have the system ask for a PIN number before a call is made. A good use is if you don't want every user on the system to be able to call international destinations. This can be done with a single PIN or multiple PINs by using the "PIN Number APP".

#### To use a single PIN number for all calls

Before the bridge action on the outbound route add the following actions

action	set	pin	_number=(Whatever	pin	number	you	choose)
action	lua	pin	number.lua				

#### To use the PIN Number App to manage multiple PINs

- First enable access to the "PIN Number" app by giving permissions to the group of users you want to have access in Advanced > Group Manager. Make sure the "PIN Number" App is displayed in the menu by selecting the groups that can view it in Advanced > Menu Manager.
- Set the PINs you would like to use in **Apps > PIN Numbers**

Before the bridge action on the outbound route add the following actions

action	set	<pre>pin_number=database</pre>
action	lua	pin_number.lua

### Which gateway is my call using?

If you want to know the gateway your call is using there is currently no way to do this with

Pagina 3 / 4 © 2024 Business-ISP <support@business-isp.nl> | 08-05-2024 23:47 URL: https://faq.business-isp.nl/index.php?action=faq&cat=127&id=3004&artlang=nl

FusionPBX's GUI. Instead you can do it this way.

• Go to **Advanced -> Command** and in the **switch** command dropdown section type

show channels as xml and then press the execute button.

• In the output that is returned, look for the string **sofia/gateway/ and the gateway name.** This is the gateway your call is using.

Next Previous

Unieke FAQ ID: #4003 Auteur: Helpdesk Laatst bijgewerkt:2022-11-28 09:34